

Tripple-output Programmable DC Power Supply



30V-3A * 3CH or 30V-6A * 3CH or 60V-3A * 3CH



Optional FTL3006-3 30V/6A * 2CH, 6V/3A *1CH

- 2U half-rack instrument delivers up to 540 W of power with low ripple and noise, or 180 W per channel;
- Linear type high resolution, high precision (1mV/1mA), high stability DC power supply;
- Capability to do series or parallel, or tracking among the channels;
- Monitor the voltage and current output in real time for all channels;
- All channels are individually controllable;
- Save and recall up to 40 groups of V/I setups;
- Voltage remote sense compensation;
- Output timer (0.1 ~ 3600 seconds);
- Overvoltage, overtemperature protections;
- Standard RS232, USB, support SCPI commands;
- Intelligent fan control, reduces noise.

General

FTL tripple-output series linear DC power supplies provide three individually controllable output channels, which can be operated in series, parallel or tracking mode. The 2U half-rack device delivers up to 540 W of power with low ripple and noise, or 180 W per channel, and offers functionalities such as remote sense, output timer, channel max voltage, overvoltage and overtemperature protections etc.. The instrument comes standard with RS232, USB ports, supports SCPI programming commands.

Model options

Model Name	CH1		CH2		CH3	
	Volta ge	Current	Volta ge	Current	Volta ge	Current
FTL3003-3	30V	3A	30V	3A	6V	3A
FTL3006-3	30V	6A	30V	6A	6V	3A
FTL6003-3	60V	3A	60V	3A	6V	3A
FTL3003-3X	30V	3A	30V	3A	30V	3A
FTL3006-3X	30V	6A	30V	6A	30V	6A

FTL Tripple-output Series

FTL6003-3X	60V	3A	60V	3A	60V	3A
------------	-----	----	-----	----	-----	----

Specifications

Model		FTL3003-3	FTL3006-3	FTL6003-3	FTL3003-3X	FTL3006-3X	FTL6003-3X
Rated Output	Voltage	0...30V*2/0...6V*1	0...30V*2/0...6V*1	0...60V*2/0...6V*1	0...30 V* 3	0...30 V* 3	0...60 V* 3
	Current	0...3 A* 3	0...6A*2/0...3A*1	0...3 A* 3	0...3 A* 3	0...6 A* 3	0...3 A* 3
Load	Voltage	≤0.01%+3mV					
Regulation	Current	≤0.01%+3mA					
Line Regulation	Voltage	≤0.01%+3mV					
	Current	≤0.01%+3mA					
Set Resolution	Voltage	1mV					
	Current	1mA					
Readback	Voltage	1mV					
Resolution	Current	1mA					
Set Accuracy	Voltage	≤0.03%+10mV					
	Current	≤0.1%+5mA	≤0.1%+8mA	≤0.1%+5mA	≤0.1%+5mA	≤0.1%+8mA	≤0.1%+5mA
Readback	Voltage	≤0.03%+10mV					
Accuracy	Current	≤0.1%+5mA	≤0.1%+8mA	≤0.1%+5mA	≤0.1%+5mA	≤0.1%+8mA	≤0.1%+5mA
Ripple Noise	Voltage	≤2mVrms					
	Current	≤5mArms					
Serial/Parallel	Voltage	≤0.02%+5mV	≤0.02%+10mV	≤0.02%+5mV	≤0.02%+10mV	≤0.02%+10mV	≤0.02%+5mV
Set Accuracy	Current	≤0.1%+30mA					
Memory	Save/Call	40 Goups of Setups					
	Function	Timing power off					
Timer	Range	0.1 s~ 3600 s					
	Resolution	0.1 s					
Work Temp.		0 ~ 40°C					
Dimension (W* H* D)	mm	255*110*380	255*110*380	255*110*380	255*110*480	255*110*480	255*110*480
Carton(W*H*D)	mm	325*210*475	325*210*475	325*210*475	325*210*575	325*210*575	325*210*575
N.W.	kg	8.5	8.5	8.5	11	11	11
G.W.	kg	10	10	10	13	13	13

Made in broke – Impasse des Colchiques, 31150 Fenouillet – Tel: 05 62 79 15 14 – contact@madeinbroke.com