

Real-Time Spectrum Analyzer & Receiver

4.5/6.3 GHz Compact USB Real-Time Spectrum Analyzer

SAN-45/SAN-60

Product Brochure V1.3

2023-8-9

- Outstanding device performance and price advantage
- 9 kHz~4.5/6.3 GHz real-time spectrum analyzer/receiver
- Integrated 100 kHz-6.3 GHz analog signal generator (option)
- Equipped with preamplifier, DANL: -160 dBm/Hz, residual response: -110 dBm
- Typical phase noise: 1GHz carrier -110 dBc/Hz@10 kHz offset
- Bandwidth: 6.25 MHz, spectrum sweep speed > 20 GHz/s
- Weight: 159 grams (core module) size: 142 mm x 54 mm x 16 mm
- Highly compatible API interfaces (HTRA API) and SAStudio4 GUI
- Compatible with ARM and x86 processors, Linux and Windows operating systems
- Operating temperatures range from -20 °C/-40 °C to 70 °C (option)
- Built-in OCXO (option), temperature drift ≤ 0.15 ppm
- USB3.0/2.0 Type-C interface



SAN-45/SAN-60 Technical Specifications * (typical value)

Indicator test basis Hardware Version: R3 API: 0.50.1 FPGA: 0.50.0 MCU: 0.50.2 SAS4: 4.1.50.40

Frequency				
Frequency Range	9 kHz~4.5 GHz (SAN-45), 9 kHz~6.3 GHz (SAN-60)			
Initial Frequency Accuracy	<1 ppm, Supporting program manual correction			
Reference Clock	Internal or external, program-controlled switching, Internal TCXO aging<1 ppm/year, temperature drift≤1 ppm; internal OCXO (option), temperature drift≤0.15 ppm			
Disciplined GNSS	Support external GNSS (option) disciplines and recalculates the built-in reference clock			
Spectrum Purity				
SSB Phase Noise	dBc/Hz			
Carrier Frequency	500 MHz	1 GHz	3 GHz	6 GHz (SAN-60)
1 kHz	-109.3	-104.4	-96.5	-90.2
10 kHz	-117.4	-111.3	-100.3	-98.4
100 kHz	-117.2	-109.3	-98.5	-96.6
1 MHz	-131.2	-129.5	-124.4	-119.6
Residual Response Spurious Rejection on dBm	Frequency Range	R.L.=0 dBm	R.L.=-20 dBm	R.L.=-50 dBm
RBW =1 kHz	100 kHz~100 MHz	<-85	<-105	<-100
Positive Peak Detector	100 MHz~4.5 GHz	<-85	<-105	<-120
Residual Response Spurious Rejection off dBm; RBW =1 kHz	100 MHz~6.3 GHz	<-85	<-105	<-120
Positive Peak Detector	100 kHz~100 MHz	<-85	<-95	<-115
	100 MHz~4.5 GHz	<-85	<-95	<-100
	100 MHz~6.3 GHz	<-77	<-95	<-110
Image Frequency Suppression	>90 dBc (spurious rejection on), >35 dBc (spurious rejection off, typical value)			
Local Oscillator Related Spurious	<-65 dBc (Offset Center Frequency +/- (N/M)*125 MHz, N/M = 1,2,3,4,5...)			
Linearity				
IIP3 (dBm) 2 MHz step -6 dBfs/Tone	1 GHz		3 GHz	6 GHz (SAN-60)
R.L.= 20 dBm	48.7		41.8	37.6
R.L.= 0 dBm	27.6		27.6	24.5
R.L.= -20 dBm	9.2		8.7	4.6
R.L.= -50 dBm	-28.1		-26.8	-28.3
IIP2 (dBm) 2 MHz step -6 dBfs/Tone	1 GHz		2 GHz	3 GHz (SAN-60)
R.L.= 20 dBm	>77		>82	>82
R.L.= 0 dBm	>77		>77	>77
R.L.= -20 dBm	>67		>67	>67
R.L.= -50 dBm	>62		>62	>67
Signal Processing				
Analysis Bandwidth	Maximum 6.25 MHz, Decimate Factor:1			
IQ Data	7.8125 MSPS Decimate factor: 1,2,4,8,16,32,64,128,256 supported (FPGA), 9 grades in total 14bit or 12bit ADC processed by DSP and output with 8bit/16bit/32bit width			
Storage Depth	The built-in memory depth is 128 Mbytes Supports continuous and uninterrupted storage when the data generation rate is less than the bus bandwidth, and the storage depth is only limited by the hard disk capacity			
External trigger response	Maximum frequency response 500 times/sec			
Analog IF output	Not supported			

Amplitude				
Maximum safe input power (CW)	26 dBm	30 MHz~4.5 GHz/6.3 GHz the preamplifier off (R.L. \geq 0 dBm)		
	10 dBm	100 kHz~30 MHz or preamplifier on (R.L. $<$ 0 dBm)		
Maximum DC Voltage	+/-15 VDC			
Display Range	DANL~26 dBm			
Amplitude Accuracy	+/- 1.5 dB			
IF in-band spectrum ripple	+/- 1.75 dB (100 MHz analog IF bandwidth)			
Reference level (R.L.)	-50 dBm~23 dBm			
RF Preamplifiers	Frequency converting bands (frequency \geq 30 MHz) are equipped with preamplifier that can be set as automatically turn on or forcibly turn off			
VSWR	<1.7:1	30 MHz~4.5 GHz/6.3 GHz (R.L. \geq 10 dBm)		
	<2.0:1	30 MHz~4.5 GHz/6.3 GHz (R.L. \geq 0 dBm)		
	<2.5:1	30 MHz~4.5 GHz/6.3 GHz (R.L. \geq -40 dBm)		
Display Average Noise Level (DANL) dBm/Hz RBW=10 kHz RMS detector	Frequency Range	R.L.= 0 dBm (IFGainGrade = 3)	R.L.=-20 dBm (IFGainGrade = 3)	R.L.=-50 dBm (IFGainGrade = 3)
	9 kHz	<-103.6	<-114.2	<-116.2
	100 kHz~100 MHz	<-131.3	<-136.3	<-134.8
	100 MHz~3.0 GHz	<-130.3	<-148.4	<-157.3
	3.0 GHz~4.5 GHz	<-124.4	<-141.5	<-158.4
3.0 GHz~6.3 GHz	<-124.6	<-141.6	<-158.2	
Standard Spectrum Analysis				
Trace Detector	Positive peak, Negative peak, RMS, Normal, Sampling			
RBW	0.1 Hz~1 MHz			
VBW	0.1 Hz~1 MHz			
Trace Function	Clear and Write, Max Hold, Min Hold, Average, Freeze			
Data Chart	SASstudio4 software provides regular spectrum, waterfall chart, and historical trace			
Sweep speed - Standard Spectrum Analysis	75.2 GHz/s	FPGA	RBW \geq 250 kHz, B-Nuttall window, spurious rejection: Standard	
	35.2 GHz/s	FPGA	RBW \geq 250 kHz, B-Nuttall window, spurious rejection: Enhanced	
	5.4 GHz/s	FPGA	RBW=30 kHz, B-Nuttall window, spurious rejection: Enhanced	
	2.2 GHz/s	CPU	RBW=1 kHz, B-Nuttall window, spurious rejection: Enhanced	
Detection Analysis/Zero Span				
Highest Time Resolution	256 ns			
Maximum Analysis Bandwidth	6.25 MHz			
Trace Detection	Positive peak, Sampling, Averaging, RMS			
Real Time Spectrum Analysis				
FFT Analysis	Variable point FFT engine implemented by FPGA. frame rate compression and trace detection are supported. There is strictly no gap and overlap between FFT frames.			
	FFT refresh rate= 10^9 ns/(N * D * 8 ns); POI = 2*N*D*8 ns N is the number of FFT points (1024,512,256,128,64,32), and D is the decimate factor (1, 2, 4, 8...)			
	Typical Settings	FFT Refresh Rate		POI
	N = 1024, D = 1	7,629 times/sec		262.144 us
	N = 32, D = 1	244,140 times/sec		8.192 us
Real-time Analysis Bandwidth	6.25 MHz			
Window Function	B-Nuttall, FlatTop			
RBW	920 kHz-3.59 kHz (FlatTop window); 488 kHz~1.90 kHz (B-Nuttall), 9 grades for each window type			
Amplitude Resolution	0.75 dB			

Signal generator (option)					
Frequency range	100 kHz~6.3 GHz, 10 Hz for each step				
Power range	-50 dBm~0 dBm, 0.25 dB for each step				
VSWR	<2.0:1	30 MHz~6.3 GHz			
Non-harmonic spurs	<-50 dBc				
Harmonic wave	100kHz~30MHz	30MHz~1.6GHz	1.6GHz~3GHz	3GHz~3.2GHz	3GHz~6.3GHz
Second harmonic	<-10 dBc	<-10 dBc	<-20 dBc	<-20 dBc	<-20 dBc
Third harmonic and above	<-10 dBc	<-10 dBc	<-20 dBc	<-20 dBc	<-20 dBc
Signal leakage to receiver	100 kHz~30 MHz		>90 dBc		
	30 MHz~3 GHz		>80 dBc		
	3 GHz~6.3 GHz		>70 dBc		

General		
Input And Output	Power Supply	Type-C (1), dedicated power supply port, please provide 5 V 2 A peak power supply capacity Allowable voltage range: 4.75~5.25 V, ripple less than 200 mVpp
	Data	Type-C (2), USB3.0 (USB2.0 available but bandwidth limited)
	RF input	SMA (F), Input impedance 50 Ω
	External reference clock input	MCX (F), amplitude ≥ 1.5 Vpp, input impedance 330 Ω
	External trigger input	Integrated in MUXIO (Type-C), 3.3 V CMOS, input: high impedance
	External trigger output	Integrated in MUXIO, 3.3 V CMOS
	Analog IF output	Not supported
Power Consumption	Peak: 10 W, typical: 7 W~10 W, power port (5 V 2 A Max), data port (5 V 1 A Max)	
Operating Temperature (device core temperature)	0~60 °C (Standard temperature class)	
	-20~70 °C (Extended Temperature Class Option) (plastic enclosure and fan not included)	
	-40~70 °C (Wide Temperature Class Option) (plastic enclosure and fan not included)	
Storage Temperature (ambient temperature)	-20~70 °C	
	-40~85 °C (Extended temperature class and wide temperature options) (plastic enclosure and fan not included)	
Weight and size	Size: 142 mmx54 mmx16 mm, weight:159 g (Excluding protective case and structural fittings, including connector length) Size: 156 mmx62 mmx22 mm, weight:296 g (Including protective case and structural fittings, including connector length)	
Accessories	Flash disk×1, USB cable×2, power adaptor×1	

*The typical values of the indicators are applicable for the following conditions: (1) Start up and warm up for 20 minutes; (2) Ambient temperature 25 °C (core temperature 50 °C); (3) Standard sweep mode-Spurious rejection on; (4) 6.25 MHz analysis bandwidth and IFGainGrade=3

HAROGIC®

Website: www.harogic.eu

Email: info@harogic.eu

Telephone: +359 887 383 850